

2	Iudul Artikel	· Modelling Ontical Waveguide Bends by the Method of Lines
	Penulis	: Ary Syahriar, Nabil Rayhan Syahriar, Jusman Syafiie Djamal.
	Nama Jurnal	: Telkomnika
	Volume Jurnal	: 16
	Nomor Jurnal	: 4
	Tahun Terbit Jurnal	: 2018
	Halaman	: 1490 – 1499
	ISSN	: 1693 – 6930
	Penerbit	: Institute of Advnaced Engineering and Science

Komentar dari Reviewer :

Mohon klarifikasi perbedaan kemiripan dengan disertasi, sebagai contoh: - Disertasi: Q is a tridiagonal matrix defined by - Karya ilmiah ini: Q is a tri-diagonal matrix defined by ... -Disertasi: Figure 3.16. Input and output field distribution of the fundamental mode after travelling around a waveguide bend of radius 5000 - Karya ilmiah ini: Figure 5. Input and output field distribution of the fundamental mode after travelling around a waveguide bend of radius 5000 PO-PAK: Mengingat publikasi ilmiah dari hasil penelitian 53 merupakan karya state of the art dari suatu bidang keilmuan dan juga mengingat kepatutan maka karya ilmiah yang dapat dinilai untuk usulan kenaikan jabatan akademily'pangkat adalah yang berbeda dengan isi bab disertasi/tesis.

Revisi (Klarifikasi/Penjelasan) :

Paper ini diturunkan dari metode yang kami kembangkan dengan menggunakan The Method of Lines yang merupakan Semi FDTD dan syarat batas yang berbeda. Untuk kategori Bend Waveguides merupakan struktur Waveguide yang kompleks sehingga pemodelan menggunakan metode transformasi koordinat dan menggunakan syarat batas yang berbeda akan menghasilkan pola yang berbeda juga. Metode yang digunakan sama dengan yang dikembangkan di thesis tetapi penekanan pada radiation mode dan syarat batas pada paer ini berbeda dari pendekatan yang dilakukan di Thesis.



Telkomnika 8

Q

Country	Indonesia - IIII SIR Ranking of Indonesia	12
Subject Area and Category	Engineering Electrical and Electronic Engineering	10
Publisher	Institute of Advanced Engineering and Science (IAES)	H Index
Publication type	Journals	
ISSN	16936930, 2087278X	
Coverage	2011-2020	
Scope	TELKOMNIKA (Telecommunication Computing Electronics and Control) is a peer reviewed International Journal in English June, September and December). The aim of TELKOMNIKA is to publish high-quality articles dedicated to all aspects of th field of electrical engineering. Its scope encompasses the engineering of signal processing, electrical (power), electronics telecommunication, computing and informatics which covers, but not limited to, the following scope: Signal Processing[Telecommunication[] Instrumentation & Control[] Computing and Informatics[]	n published four issues per year (March, ne latest outstanding developments in the s, instrumentation & control, .] Electronics[] Electrical[]
?	Homepage	
	How to publish in this journal	
	Contact	
	\bigcirc Join the conversation about this journal	











Cites per Doc









Vol 16, No 4

Optimum Work Frequency for Marine Monitoring Based on Genetic Algorithm Fahraini Bacharuddin, Hadi Wuryanto, Yuliza Yuliza, Beny Nugraha	<u>PD</u> 1551-155
Modelling Optical Waysquide Bends by the Method of Lines	PD
Ary Syahriar, Nabil Rayhan Syahriar, Jusman Syafiie Djamal	1490-149
Beam Steering using the Active Element Pattern of Antenna Array	PD
Norun Abdul Malek, Othman Omran Khalifa, Zuhairiah Zainal Abidin, Sarah Yasmin Mohamad, Nur Aqilah Abdul Rahman	1542-155
Specific Absorption Rate Assessment of Multiple Microstrip Patch Antenna Array	<u>PD</u>
Nur Ilham Aliyaa Ishak, Norhudah Seman, Noor Asmawati Samsuri	1500-150
Design and Fabrication of the Novel Miniaturized Microstrip Coupler 3dB Using Stepped Impedance Resonators for the ISM Applications	<u>PD</u>
Azzeddine Sardi, Jamal Zbitou, Ahmed Errkik, Mohamed Latrach	1560-156
Bi-directional Beams Waveguide Slotted Antenna at Millimeter Wave	<u>PC</u>
Muataz W. Sabri, Noor A. Murad, Mohammed K.A. Rahim	1515-152
Switchable Wideband Metamaterial Absorber and AMC reflector for X-band Applications and Operations	<u>PC</u>
M. M. Gajibo, M. K. A. Rahim, N. A. Murad, O. Ayop, H. A. Majid	1535-154
Distributed Control System Applied in Temperatur Control by Coordinating Multi-loop Controllers	<u>PC</u>
Edi Rakhman, Feriyonika Feriyonika	1568-157
Measurement of Shear Strain in Map Liquefaction Area for Earthquake	<u>PC</u>
Mitigation in Bengkulu City Muhammad Farid Arif Ismul Hadi	1507-160
ריעוומווווופע דמווע, אווו בזווער וופטו	1397-100
Deep Learning for Tuning Optical Beamforming Networks Herminarto Nugroho, Wahyu Kunto Wibowo, Aulia Rahma Annisa, Hanny Megawati Rosalinda	1607-161
	<u>P(</u>
Development of Fall Risk Detector for Elderly Nor Aini Zakaria. Nur Amalina Rashid, Muhammad Amir Asa'ari	1577-158
Metamodel-based Optimization of a PID Controller Parameters for a Coupled-	Pr
tank System Marwan Nafea, Abdul Rasyid Mohammad Ali, Jeevananthan Baliah, Mohamed Sultan Mohamed Ali	1590-159
Path Tracking on Autonomous Vehicle for Severe Maneuvre	<u>PC</u>
Zulkarnain Zulkarnain, Hairi Zamzuri, M. H. M. Ariff, Umar Zakir Abdul Hamid	1583-158
Hybrid Head Tracking for Wheelchair Control Using Haar Cascade Classifier and KCF Tracker	PC
Fitri Utaminingrum, Yuita Arum Sari, Putra Pandu Adikara, Dahnial Syauqy, Sigit Adinugroho	1616-162
Implementation of Fuzzy-PD for Folding Machine Prototype Using LEGO EV3	<u>P[</u>
Wahyu S. Pambudi, Titiek Suheta	1625-163
Bull Sperm Motility Measurement Improvement Using Sperm Head Direction	<u>PC</u>
Aligie Akbar Akbar, Eros Sukmawati, Dwi Utami, Muhammad Nuriyadi, Iwan Awaludin, Priyanto Hidayatullah	1642-164
	<u>P(</u>
Color Distribution Analysis for Ripeness Prediction of Golden Apollo Melon Usman Ahmad, Dwi Pamungkas Bermani, Mardison Mardison	1659-166
	<u>P</u> [
Development of Pose Estimation Algorithm for Quranic Arabic Word Luqman Naim Mohd Esa, Malik Arman Morshidi, Syarah Munirah Mohd Zailani	1633-164
Determining Best Window Size for an Improved Gabor Transform in EMG Signal Analysis	<u>P[</u>
E.F. Shair, S.A. Ahmad, A.R. Abdullah, M.H. Marhaban, S.B. Mohd Tamrin	1650-165
A Model to Predict The Live Bodyweight of Livestock Using Back-Propagation Algorithm	<u>P</u> [
- Inggih Permana, Ria Agustina, Endah Purnamasari, Febi Nur Salisah	1667-167
The Forecasting Technique Using SSA-SVM Applied to Foreign Tourist Arrivals to Bali	<u>PC</u>
Yosep Oktavianus Sitohang, Yudhie Andriyana, Anna Chadidjah	1679-168
	<u>PC</u>
Designing Fuzzy Expert System to Identify Child Intelligence	1000 100
riunanida Banrul Vium, vitri Lundjungsari	1688-169

Vol 16, No 4

Optimizing Laying Hen Diet using Multi-Swarm Particle Swarm Optimization Gusti Abmad Fanshuri Alfarisy, Wayan Firdaus Mahmudy, Muhammad Halim Natsir	<u>PDF</u> 1712-1723
Significance of Speech Intelligibility Assessors in Medium Classroom Using Analytical Hierarchy Process	<u>PDF</u>
Mohyacar Harun, Khairunnisa Mohd Yusof, Mohamad Ngasri Dimon, Puspa Inayat Khalid, Siti Zaleha Abdul Hamid	1673-1678
The Development of Javanese Language Teaching Materials Through Introduction of Java Scripts Using Artificial Neural Network	PDF
Siswo wardoyo, Kuntari W., Anggoro S. Pramudyo, Suhendar Suhendar, Syarif Hidayat	1697-1703
News Reliability Evaluation using Latent Semantic Analysis	<u>PDF</u>
Guo Xiaoning, Tan De Zhern, Soo Wooi King, Tan Yi Fei, Lam Hai Shuan	1704-1711
Biometric Analysis of Leaf Venation Density Based on Digital Image	<u>PDF</u>
Agus Ambarwari, Yeni Herdiyeni, Irman Hermadi	1735-1744
Classification Based on Latent Dirichlet Allocation Retno Kusumaningrum, Satriyo Adhy, Suryono Suryono	1752-1759
	<u>PDF</u>
Applied Healthcare Knowledge Management for Hospital in Clinical Aspect Sevenpri Candra, Ichsan Kurniawan Putrama	1760-1770
Semi-Supervised Keyphrase Extraction on Scientific Article using Fact-based	<u>PDF</u>
Sentiment Felix Christian Jonathan, Oscar Karnalim	1771-1778
Algorithm for Predicting Compound Protein Interaction Using Tanimoto	PDF
Isnan Mulia, Wisnu Ananta Kusuma, Farit Mochamad Afendi	1785-1792
Combining Two Models of Successful Information System Measurement	PDF
Pualam Dipa Nusantara, Nyoman Ayu Gayatri, Martin Suhartana	1793-1800
Implementation of Augmented Reality as Information and Promotion Media on Dieng Tourism Area	<u>PDF</u>
Banu Nur Affan, Agus Suryanto, Arief Arfriandi	1818-1825
Multi-class K-support Vector Nearest Neighbor for Mango Leaf Classification	<u>PDF</u>
Eko Prasetyo, R. Dimas Adityo, Nanik Suciati, Chastine Fatichah	1826-1837
Integrated Social Media Knowledge Capture in Medical Domain of Indonesia Kridanto Surendro, Dicky Prima Satya, Farrell Yodihartomo	<u>PDF</u> 1846-1856
Development of Leaf Area Meter Using Open CV for Smartphone Application	<u>PDF</u>
Tony K. Hariadi, Zulfan Fadholi, Anna NN Chamim, Nafi A Utama, Indira Prabasari, Slamet Riyadi	1857-1863
Fingerprint Pattern of Matching Family with GLCM Feature	PDF
Bahtiar Imran, Karya Gunawan, Muhammad Zohri, Lalu Darmawan Bakti	1864-1869
Identifying Citronella Plants From UAV Imagery Using Support Vector Machine Candra Dewi, Achmad Basuki	<u>PDF</u> 1877-1885
An Early Drowning Detection System for Internet of Things (IoT) Applications	<u>PDF</u>
Muhammad Ramdhan MS, Muhammad Ali, Paulson Eberechukwu N, Nurzal Effiyana G, Samura Ali, Kamaludin M.Y	1870-1876
Token-based Single Sign-on with JWT as Information System Dashboard for Government	<u>PDI</u>
I Putu Arie Pratama, Linawati Linawati, Nyoman Putra Sastra	1745-1751
A Novel Forecasting Based on Automatic-optimized Fuzzy Time Series Yusuf Privo Anggodo, Wayan Firdaus Mahmudy	<u>PDF</u> 1809-1817
Analysing Signal Strength and Connection Speed in Cloud Networks for	<u>PDF</u>
Gananda Hayardisi, Kudang Boro Seminar, Arief Ramadhan	1779-1784
Backtracking Search Optimization for Collaborative Beamforming in Wireless Sensor Networks	PDF
N.N. Ahmad Nazri, N.N. Nik Abd Malik, L. Idoumghar, N.M. Abdul Latiff, S. Ali	1801-1808

Vol 16, No 4

1845
PDF
1893
<u>PDF</u>
1900
-

TELKOMNIKA Telecommunication, Computing, Electronics and Control ISSN: 1693-6930, e-ISSN: 2302-9293 Universitas Ahmad Dahlan, 4th Campus, 9th Floor, LPPI Room Jl. Ringroad Selatan, Kragilan, Tamanan, Banguntapan, Bantul, Yogyakarta, Indonesia 55191 Phone: +62 (274) 563515, 511830, 379418, 371120 ext. 4902, Fax: +62 274 564604

02215228

View TELKOMNIKA Stats

See discussions, stats, and author profiles for this publication at: https://www.researchgate.net/publication/326544466

Modelling Optical Waveguide Bends by the Method of Lines

Article · August 2018 DOI: 10.12928/TELKOMNIKA.v16i4.5191

Some of the authors of this publication are also working on these related projects:



Dark and bright soliton in fiber optics View project

VLC UAI View project

1490

Modelling Optical Waveguide Bends by the Method of Lines

Ary Syahriar^{*1}, Nabil Rayhan Syahriar², Jusman Syafiie Djamal³

^{1,3} Electrical Engineering Department, Faculty of Science and Technology University al Azhar Indonesia, Jakarta Indonesia

² Mechanical Engineering Department, Bandung Institute of Technology *Corresponding author, e-mail: ary@uai.ac.id

Abstract

A rigorous analytical and semi analytical method of lines has been used to calculate the transverse-electric field attenuation coefficient of guided mode as it travels in waveguide bends structure. Both approaches then were compared to get a better understanding on how the attenuation behaves along single curve waveguides with constant radius of curvature. The Helmholtz Equation in polar coordinate was transformed into a curvalinier coordinate to simulate the waveguide bends using the method of line analysis. The simple absorption boundary conditions are used into the method of lines to demonstrate evanescent field of the guided mode nature as its travels in waveguide bends structures. The results show that a reasonable agreement between both theoretical approaches.

Keywords: Optical waveguide bends, Method of lines, The transverse-electric field attenuation coefficient

Copyright © 2018 Universitas Ahmad Dahlan. All rights reserved.

1. Introduction

One of the most important optical integrated devices building blocks is waveguide bends because it defines the overall size of integrated optics in single subtrates. Waveguide bends are required in many basic optical structures, including directional couplers, modulators, ring resonators [1], arrayed waveguide filters [2], optical delay lines [3], S-bend attenuators [4]. and Mach-Zehnder interferometers. However, waveguide bends experience loss as the guided mode enters the curved section which depends on confinement factors and radius of curvature. The loss can be minimized by increasing the mode confinement i.e. by increasing the refractive index differences between core and cladding layers or by decreasing radius of curvatures. Increasing mode confinement will increase the coupling losses when waveguide is coupled into the fiber optics and decreasing radius of curvature will increase the overall integrated optics size. In a silica-based waveguide, there is normally only a very slight variation in refractive index across the cross-section, to allow low loss coupling to a single mode fibre. The slight variation in index is most helpful as it permits the vector wave equation to be replaced by a scalar equation in which the electric field is represented by one vector component. This simplification is known as the weak-guidance approximation. Therefore a precise knowledge on bend waveguides characteristics become important to design a compact integrated optical systems.

So far, a number of efficient numerical techniques have been proposed for the analysis of optical waveguides. These include the finite difference method (FDM), the finite element method (FEM), the beam propagation method (BPM), and the method of lines (MoL) [5]. The finite difference method is the oldest numerical method for solving partial differential equations. It is simple to program and easily applied to non-homogenous refractive index profiles. This method subdivides the domain into many subregions, in which the partial derivatives are replaced by finite difference operators. A set of linear equations are then solved to obtain the eigenvalues. The drawback of the FDM is it offers less flexibility in the modeling of the domain since the subregion is normally rectangular in shape [6]. The finite element method (FEM) can model the most intricate domain geometries. In FEM, the waveguide cross section is divided into surface or volume elements and the field in each element is approximated by a polynomial. The field continuity conditions are imposed on all interfaces between the different elements. A variational expression for Maxwell's equations then is employed to obtain an eigenvalue matrix equation which is solved by standard methods. This method requires a more complex

programming structure and is more demanding in both computer time and memory [7]. The beam propagation method (BPM) has been used to analyze various two- and three-dimensional optical devices. The original BPM used an FFT algorithm and solved a paraxial scalar wave equation. The basic idea of the BPM is to represent the electromagnetic field by a superposition of plane waves propagating in homogenous media. The advantages of the BPM are that it can be applied to a structure with an arbitrary cross-section, and that both guided and radiative waves are included in the analysis. However since the formulation is derived under the assumption that the refractive index variation in the transverse direction is very small, the FFT-BPM cannot be applied to structures with large index discontinuities [6].

The method of lines (MoL) has been proved to be a very useful tool for the analysis of general waveguide systems [8]. It is a semi analytical method, in which the wave equation is discretized as far as necessary in the transverse direction and solved analytically in the longitudinal direction, which results in less computational effort. An accurate result can be obtained since the MoL behaves in a stationary fashion and convergence is monotonic [9]. Discontinuous fields can be described accurately because the interface conditions are included in the calculation. Furthermore, the MoL is relatively easy to implement using computer numerical methods. In this paper we compare two different approaches, namely a simple quasianalytic theory based on integration of a phenomenological absorption coefficient, and the method of lines (MoL). Both are applied to a number of different waveguide bend curvatures.

In this paper we applied the method of lines with third order absorbing boundary condition to analyse weakly guiding optical waveguides bends characteristics. For the first approximation we have transformed the Helmholtz wave equation in polar co-ordinates to Cartesian coordinates to simplify the discretisation of waveguide structures. In the process we compared the results with analytical methods as the correct references that has been developed previously. We found that the MoL results are in good agreement with analytical methods. The discrepencies arised from differents radius of curvature used in the calculation and the choices of absorbing boundaries parameters.

2. Research Method

2.1. Analytical Approach

To analyse the effect of a waveguide bend, consider a bend formed by a circular arc with radius of curvature *r* as shown in Figure 1. It is assumed that only the fundamental mode propagates in the guide. If the radius of curvature is large enough ($r \rightarrow \infty$), then the properties of the mode are effectively those of a mode traveling in a straight guide. However, as *r* decreases, attenuation is expected to occur. Let *P*(*s*) be the total power carried by the mode at any point *s* along the bend. Assuming that the rate of power loss is proportional to the power carried by the mode at that point, we can write:



Figure 1. Section of a curved planar waveguide

$$\frac{dP(s)}{ds} = -\alpha P(s) \tag{1}$$

where α is the attenuation coefficient. Provided α is constant, equation 1 has the solution:

$$P(s) = P(0)e^{-\alpha s} \tag{2}$$

Marcatili and Miller have shown that the attenuation coefficient is indeed constant for a fixed radius, and can be expressed as [10]:

$$\alpha = C_1 e^{-C_2 r} \tag{3}$$

where C_1 and C_2 are functions of the waveguide parameters but are independent of *r*. Equation 3 shows that the attenuation coefficient increases exponentially with decreasing bending radius; however, if the radius of curvature become large enough the attenuation becomes negligible. It also shows that the change of α with *r* is dominated by the value of C_2 , which (for a weakly-guiding guide) is given by [11]:

$$C_2 = \frac{2\pi \left(2\Delta n_{eff}\right)^{\frac{3}{2}}}{\sqrt{n_2}} \tag{4}$$

Here $\Delta n_{\text{eff}} = n_{\text{eff}} - n_2$, where n_2 is the refractive index of the cladding.

The C_2 value also provides a method for characterising mode confinement, which is useful when investigating techniques for reducing bend losses. Equation 3 shows that α is also affected (but less strongly) by the value of the coefficient C_1 , which is defined as [11]:

$$C_1 = \frac{1}{2Z_c} \frac{\chi_l}{\chi_t}$$
(5)

where the parameters Z_c , χ_t , and χ'_l are given by:

$$Z_{c} = \frac{n_{2}}{2\lambda} \left[h + 2\sigma \cos(\frac{\kappa h}{2}) \right]^{2}$$
(6)

$$\chi_t = \frac{h}{2} + \frac{1}{2\kappa} \sin(\kappa h) + \sigma \cos^2(\frac{\kappa h}{2})$$
(7)

and,

$$\chi_{l} = \frac{\sigma}{2} \cos^{2} \left[\frac{\kappa h}{2} \right] e^{\frac{h}{\sigma}}$$
(8)

where σ is given by:

$$\frac{1}{\sigma} = \sqrt{\beta^2 - k_0 n_2^2} \tag{9}$$

and *h*, γ and κ have their usual meanings [12].

The C_1 coefficient as defined in equation 4 is not a direct function of Δn_{eff} , but is related to the difference between the propagation constant within the guide and the cladding refractive index n_2 . Additionally, the C_1 coefficient is strongly model dependent, and so can be used to calculate the guide shape and other parameters. The above formulation of the C_1 and the C_2 coefficients was based on the derivation made by Marcatili et.al [10] and later adopted by Minford et.al [11]. However, two other formulations have been provided by Lee [12] and Marcuse [13,14]. Lee's version of the C_1 and the C_2 coefficients is as follows [12]: ISSN: 1693-6930

$$C_{1} = \frac{2\gamma^{2}}{k_{o}n_{2}(\gamma h+2)} \cos^{2}(\frac{\kappa h}{2})e^{\gamma h}$$
(10)

and,

$$C_2 = \frac{2\gamma(n_{eff} - n_2)}{n_2}$$
(11)

Here, k_0 , κ , γ , and *h* have their usual meaning. In a similar way, Marcuse's version of the coefficients is as follows [14]:

$$C_{1} = \frac{2\gamma^{2}}{\beta(2+\gamma\hbar)(n_{1}^{2}-n_{2}^{2})k_{o}^{2}}\exp(\gamma\hbar)$$
(12)

and,

$$C_2 = \frac{2}{3} \frac{\gamma^3}{\beta^2}$$
(13)

here, the propagation constant is defined as $\beta = k_o n_{eff}$. It might be expected that these different formulations would give similar results; however, this was not found to be the case.

2.2. Method of Lines

In this analysis we begin by considering the behaviour of a guided mode as it travels around a bend of constant curvature. Figure 2 shows a schematic of the geometry. The waveguide has a constant radius of curvature r, which is measured from the centre of the guide. The guide is of width h, which is assumed to be much less than r and is centred on a computational window of width w. The core and cladding refractive indices are given by n_1 and n_2 respectively.



Figure 2. Discretisation of a planar waveguides bends by the MoL

Assuming a *y*-polarised electric field, the Helmholtz wave equation can be written in polar co-ordinates as [15]:

$$\frac{1}{\rho}\frac{\partial E_{y}}{\partial \rho} + \frac{\partial^{2} E_{y}}{\partial \rho^{2}} + \frac{1}{\rho^{2}}\frac{\partial^{2} E_{y}}{\partial \varphi^{2}} + k_{o}^{2}n^{2}E_{y} = 0$$
(14)

To implement a numerical solution of equation 14 a modification must be made. It involves changing the co-ordinates to a local co-ordinate system that follows the centre of the waveguide along the propagation direction [15]. This change also allows the possibility of analysing the field profile at the local cross-section. By making the substitution:

$$\rho = x + r
s = r\varphi$$
(15)

Equation 14 may be transformed to:

$$\frac{\partial^2 E_y}{\partial s^2} + (1+cx)^2 \frac{\partial^2 E_y}{\partial x^2} + c(1+cx) \frac{\partial E_y}{\partial x} + (1+cx)^2 k_0^2 n^2(x) E_y = 0$$
(16)

where the constant c = 1/r represents the waveguide curvature. Note that it is easy to see how equation 16 reduces to the scalar wave equation for a straight waveguide when c=0. There are some advantages using equation 16. Firstly, the computational window can be restricted because the centre is along the path of the waveguide. Secondly, the index profiles need not be altered as the radius of curvature changes, in contrast to the other methods which use the modified index profile [15]. To solve equation 16 by the MoL, the equation is now discretised using the finite difference operator, by putting:

$$\frac{\partial^2 E_y}{\partial x^2} \approx \frac{E_{i+1} - 2E_i + E_{i-1}}{(\Delta x)^2}$$
(17)

and:

$$\frac{\partial E_y}{\partial x} \approx \frac{E_{i+1} - E_{i-1}}{2\Delta x}$$
(18)

If this is done, equation 16 can be written in matrix form as:

$$\frac{d^2\vec{E}}{ds^2} + \vec{Q}\vec{E} = 0 \tag{19}$$

where $\vec{E} = [E_1, E_2, E_3, \dots, E_N]^t$ is a column vector containing discretised values of the field $E_v(x)$, at the points x_1, x_2, \dots, x_N , and \vec{Q} is a tri-diagonal matrix defined by :

$$\vec{Q}^{2} = \frac{1}{\left(\Delta x\right)^{2}} \begin{bmatrix} -2(1+cx_{1})^{2} & (1+cx_{1})^{2} & 0 & 0\\ (1+cx_{2})^{2} & -2(1+cx_{2})^{2} & (1+cx_{2})^{2} & 0\\ \vdots & \vdots & \ddots & \vdots\\ 0 & 0 & (1+cx_{N})^{2} & -2(1+cx_{N})^{2} \end{bmatrix} +$$
(20)

$$\frac{1}{2\Delta x} \begin{bmatrix} 0 & c(1+cx_1) & 0 & 0 \\ -c(1+cx_2) & 0 & c(1+cx_2) \\ \dots & \dots & \dots & \dots \\ 0 & 0 & -c(1+cx_N) & 0 \end{bmatrix} + k_0 \begin{bmatrix} (1+cx_1)^2 n^2 & 0 & 0 & 0 \\ 0 & (1+cx_2)^2 n^2 & 0 & 0 \\ \dots & \dots & \dots & \dots \\ 0 & 0 & 0 & (1+cx_N)^2 n^2 \end{bmatrix}$$

Assuming that there is no back-reflection, the general solution for constant matrix elements has the form:

$$\vec{E} = \vec{T}e^{-j\vec{\beta}s}\vec{T}^{-1}\vec{E}_{inp}$$
⁽²¹⁾

where \vec{T} is a matrix containing the eigenvectors of Q arranged in columns, $\vec{\beta}$ is a diagonal matrix containing the eigenvalues of \vec{Q} , and \vec{E}_{inp} is the input field vector. One of the most important parameters associated with the waveguide is the fractional power that remains in the core at point *z*. This power is approximately given by the overlap integral:

$$P(z) = \left| \int_{-\infty}^{\infty} E(x,0)E(x,z)dx \right|^2$$
(22)

where E(x,0) is the input field and E(x,z) is the field at point z.

2.3. The Absorbing Boundary Condition

To calculate the modal field of the curved waveguide, it is necessary to restrict the extent of the computational window. Once again, this is done using absorbing boundary conditions. Derivation of appropriate boundary conditions in polar co-ordinate is generally rather complicated [16]. In the calculation described here, we have adopted a simpler approach, applying a straight guide boundary condition to the curved waveguide equation, by using the assumption that the radius of curvature is large enough that the mode inside the bend is similar to that of straight guide.

The absorbing boundary condition is inserted into the edge of the matrix components of equation 20 [16]. In this case, we have used the more effective third-order absorbing boundary condition, where the radical is approximated by:

$$\sqrt{1+S^2} \approx \frac{p_0 + p_2 S^2}{q_0 + q_2 S^2}$$
(23)

Differences in the choice of the coefficients, p and q, produces different families of absorbing boundary conditions. These result in differences in the angle of exact absorption of the incoming wave by the absorbing boundary layer. Table 1 shows a list of the coefficient values and absorption angles of the approximations that are most commonly used. Here, we have used the L_{∞} type of approximation.

Type of approximation	p_0	p_2	q_2	angle of exact absorption (°)	
Pade'	1.0000	-0.7500	-0.2500	0.0	
Chebyshev L^{∞}	0.9997	-0.8086	-0.3165	11.7, 31.9, 43.5	
Chebyshev points	0.9965	-0.9129	-0.4725	15.0, 45.0, 75.0	
Least square (L_2)	0.9925	-0.9223	-0.5108	18.4, 51.3, 76.6	
Chebyshev-Pade' (C-P)	0.9903	-0.9431	-0.5556	18.4, 53.1, 81.2	
Newman points	1.0000	-1.0000	0.6697	0.0, 60.5, 90.0	
Chebyshev L	0.9565	-0.9435	0.7038	26.9. 66.6. 87.0	

Table 1. Coefficients for different third-order absorbing boundary conditions, after reference [4.16]

 q_0 = 1.0000 for each approximation

3. Results and Analysis

To get a better understanding on how the guided mode evolution during its propagation inside curved waveguides; we have used two methods, i.e. an analytical theory that is assumed to be the right approach and the method of lines. In both calculations parameters of a waveguide bends with a radius 5000 μ m through an angle of 45° with different refractive index

changes have been used. Figure 3 shows the variation of C_2 calculated using equation 4 with wavelength for different values of Δn , i.e. for different degrees of waveguide confinement. These results show that C_2 increases as the confinement becomes higher and also that C_2 values generally decrease slowly at long wavelengths.



Figure 3. Variation of the parameter C_2 with wavelength, for different values of Δn as predicted by equation 4

Figure 4 (a) and (b) show a comparison of the C_1 and the C_2 values as a function of waveguide width, calculated by Marcatili's approximation of equation 4 and 5; Lee's approximation of equation 10 and 11; and Marcuse's approximation of equation 12 and 13 respectively. Here, the parameters of n_1 =1.463, n_2 =1458, λ =1.525 µm, with *h* varying from 4 µm to 7 µm, have been used.



Figure 4. A comparison of different approximations for (a) the C_1 value, and (b) the C_2 value

Figure 4 (a) shows that the C_1 coefficients of Lee's and Marcuse's expression are in a good agreement. However, Marcatili's equation gives much lower value. This might well be because of the different approaches used to derive the C_1 coefficient. The Marcatili approximation is obtained from the complex solution of the eigenvalue equation of the waveguide bend, while both Lee and Marcuse use a different approximation based on the local rate of power radiation from the bend. Furthermore, for the C_2 coefficient, Lee's and Marcatili's approximations give a good agreement, while Marcuse's approach gives apparently incorrect values. It can be concluded that Lee's expression is the most likely to be correct. This assumption will be validated later by comparison with the rigorous method of lines.

To illustrate the way in which the guided mode evolves in a curved waveguide, we first compare the input and output mode shapes obtained after travelling round a bend of radius 5000 μ m through an angle of 45°. Figure 5 (a) shows results obtained for a guide of core index 1.464, cladding index 1.458 and width 5 μ m at a wavelength of 1.525 μ m, while Figure 5 (b) shows results for a similar but less strongly confining guide which has a core index of 1.463. The calculations have been done by using the MOL scheme.





Figure 5 demonstrates that the output field profile of the mode generally extends into the cladding and its peak is reduced, so that it is gradually radiating power. The amount of the power loss depends on the degree of confinement. For example, in Figure 5(a), the output field extends into the cladding only to a very limited extent, and the input and the output field shapes are very similar. However, in Figure 5(b) the output field extends much further into the cladding due to the reduction in confinement. The degree of asymmetry also increases considerably as the confinement is reduced.

We now use the results of the method of lines calculation to estimate an effective attenuation coefficient along a uniformly curved waveguide. This can be done by using equation 1, where the $\frac{dP(s)}{ds}$ values are found by evaluating the difference in the integrated optical power across the mode in the computational area between two adjacent axial propagation steps. Figure 6 shows the attenuation coefficient found in this way as a function of bending angle φ , for the parameters Δn =0.005, 0.006, and 0.007, n_2 =1.458, λ =1.525 μ m, h=5 μ m, and r=5000 μ m.



Figure 6. Attenuation coefficient as a function of the bending angle φ , for a different degrees of confinement

In each case, the value of α is not constant, but rises gradually from zero at the start of the bend and settles to a steady-state value only after some rapid fluctuations. In early analyses, the fluctuations have been associated with transition loss [17-18]. However, recently it was demonstrated that they are merely a mathematical artefact which is inherent in numerical modelling of bends using beam propagation methods, and the steady-state value is an accurate estimate of the attenuation coefficient after the mode has settled to its final lateral position.

A comparison of the attenuation coefficients predicted by simple theory and the MoL (at large axial distance) is shown in Figure 8. In the analytical approximations, the C_1 and the C_2 coefficients needed to find the α values have been calculated by using each of the three approximations.





Figure 8 demonstrates that good agreement is obtained between the analytical form for the loss coefficient based on Lee's expression and the MoL calculation. A slight difference, however, occurs at a small radius. In contrast, Marcatili's formulation predicts a very low value of α when compared to Lee's approximation and the MoL calculation, while Marcuse's formulation predicts much higher values.

The residual discrepancies between the predictions of Lee's theory and the MoL may be explained as follows. In the MoL, the calculation results are highly dependent on a proper choice of absorbing boundary condition at the edge of the computational windows, so that unsuitable conditions give rise to significant reflection back into the computational window and hence lower apparent loss. A similar effect also appears in another numerical scheme [19].

4. Conclusion

We have investigated different analytic approximations to the local loss coefficient in waveguide bends based on constant radius of curvature, and have uncovered disagreement between several previously published analytical expressions. To verify the accuracy of the attenuation coefficient on several publish analytical expression, we have used the beam propagation algorithm based on the method of lines in polar co-ordinate. We have found reasonable agreement with the analytic approximation to the local loss coefficient based on Lee's approach. This agreement might be used to extend the calculation of loss in waveguide bends structure in modelling continuously-varying S-bends waveguides using cascaded section method. Residual disagreement is ascribed mainly to the moderate performance of the absorbing boundary conditions used to limit the range of the calculation window.

References

- [1] BE Little, ST Chu, HA Haus, J Foresi, JP Laine. Microring resonator channel dropping filters. *J. Lightwave Technol.* 1997; 15: 998-1005.
- [2] M Zirngibl, CH Joyner, LW Stulz, T Gaiffe, C Dragone. Polarization independent 8 × 8 waveguide grating multiplexers on In P. *Electron. Lett.* 1993; 29: 201-202.
- [3] RR Hayes, D Yap. GaAs spiral optical waveguides for delay-line applications. *J. Lightwave Technol.* 1993; 11: 523-528.
- [4] X Jiang, W Qi, H Zhang, Y Tang, Y Hao, J Yang, M Wang. Loss crosstalk 1 × 2 thermooptic digital optical switch with integrated S-bend attenuator. *IEEE Photon. Technol. Lett.* 2006; 18: 610-612.
- [5] F Ladouceur, JD Love. Silica-based buried channel waveguides and devices. Chapman & Hall. London. 1996.
- [6] WP Huang. Methods for modeling and simulation of guided-wave optoelectronic devices: part I: modes and couplings. EMW Publishing, Cambridge, Massachusetts, 1995.
- [7] SM Saad. Review of numerical methods for the analysis of arbitrarily-shaped microwave and optical dielectric waveguides. *IEEE Trans. on Microwave Theory and Tech.* 1985; MTT-33: 894-899.
- [8] T Itoh. Numerical techniques for microwave and millimeter-wave passive structures. John Wiley & Sons. New York. 1989.
- U Rogge, R Pregla. Method of lines for the analysis of dielectric waveguides. *IEEE J.Lightwave Technol.* 1993; LT-11: 2015-2020.
- [10] EAJ Marcatili. Bends in optical dielectric guides. Bell Syst. Tech. J. 1969; 48: 2103-2132.
- [11] WJ Minford, SK Korotky, RD Alferness. Low-loss Ti:LiNbO₃ waveguide bends at =1.3 m. IEEE J. Quantum Electron. 1982; QE-18: 1802-1806.
- [12] DL Lee. Electromagnetic principles of integrated optics. John Wiley & sons. New York. 1986.
- [13] D Marcuse. Length optimisation of an S-shaped transition between offset optical waveguides. *Appl. Opt.* 1978; 17: 763-768.
- [14] D Marcuse. Bending losses of the asymmetric slab waveguide. Bell Syst. Tech. J. 1971; 50: 2551-2563.
- [15] SJ Garth. Mode behaviour on bent planar dielectric waveguides. *IEE Proc. Optoelectron.* 1995; 142: 115-120.
- [16] TG Moore, JG Blaschak, A Taflove, GA Kriegsmann. Theory and application of radiation boundary operators. *IEEE Trans. Antenna and Prop.* 1988; 36: 1797-1812.
- [17] J Yamauchi, S Kikuchi, T Hirooka, M Nakano. Beam propagation analysis of bent step-index slab waveguide. *Elect. Lett.* 1990; 26: 822-824.
- [18] M Rivera. Lowest-order mode transmission in multimode dielectric S-bends. Opt. Quantum Electron. 1997; 29: 323-333.
- [19] J Saijonmaa, D Yevick. Beam-propagation analysis of loss in bent optical waveguides and fibers. *J. Opt. Soc. Amer.* 1983; 73: 1785-1791.

Modelling Optical Waveguide Bends by the Method of Lines

by Ary Syahriar

Submission date: 01-Nov-2020 04:00AM (UTC+0000) Submission ID: 1432458679 File name: 5191-27947-1-PB.pdf (182.67K) Word count: 4324 Character count: 21746 TELKOMNIKA, Vol.16, No.4, August 2018, pp. 1490~1499 ISSN: 1693-6930, accredited First Grade by Kemenristekdikti, Decree No: 21/E/KPT/2018 DOI: 10.12928/TELKOMNIKA.v16i4.5191

1490

Modelling Optical Waveguide Bends by the Method of Lines

Ary Syahriar^{*1}, Nabil Rayhan Syahriar², Jusman Syafile Djamal³ ^{1,3} Electrical Engineering Department, Faculty of Science and Technology University al Azhar Indonesia, ²⁴ Jakarta Indonesia ² Mechanical Engineering Departmer 35 andung Institute of Technology *Corresponding author, e-mail: ary@uai.ac.id

Abstract

A rigorous analytical and semi analytical method of lines has been used to calculate the transverse-electric field attenuation coefficient of guided mode as it travels in waveguide bends structure. Both approaches then were compared to get a better understanding on how the attenuation behaves along single curve waveguides with constant radius of curvature. The Helmholtz Equation in polar coordinate was transformed into a curvalinier coordinate to simulate the waveguide bends using the method of line analysis. The simple absorption boundary conditions are used into the method of lines to demonstrate evanescent field of the guided mode nature as its travels in waveguide bends structures. The results show that a reasonable agreement between both theoretical approaches.

Keywords: Optical waveguide bends, Method of lines, The transverse-electric field attenuation coefficient

Copyright © 2018 Universitas Ahmad Dahlan. All rights reserved.

1. Introduction

One of the most important optical integrated devices building blocks is naveguide bends because it defines the overall size of integrated optics in single subtrates. Waveguide 82nds are required in many basic optical structures, including directional couplers, modulators, ring resonators [1], arrayed waveguide filters [2], optical delay lines [3], S-bend attenuators [4]. and Mach-Zehnder interferometers. However, waveguide bends experience loss as the guided mode enters the curved section which depends on confinement factors and radius of curvature. The loss can be minimized by increasing the mode confinement i.e. by increasing the refractive index differences between core and cladding layers or by decreasing radius of curvatures. Increasing mode confinement will increase the coupling losses when waveguide is coupled into the fiber optics and decreasing radius of curvature will increase the overall integrated optics size. In a silica-based waveguide, there is normally only a very slight variation in refractive index across the cross-section, to allow low 13 coupling to a single mode fibre. The slight variation in index is most helpful as it permits the vector wave equation to be replaced by a scalar equation in which the electric field is represented by one vector component. This simplification is known as the weak-guidance approximation. Therefore a precise knowledge on bend waveguides charactes stics become important to design a compact integrated optical systems.

So far, a number of efficient numerical techniques have been proposed for the analysis of optical waveguides. These include the finite difference method (FDM), the finite eler **37** t method (FEM), the beam propagation method (BPM), and the method of lines (MoL) [5]. The finite difference method is the oldest numerical method for solving partial differential equations. It is simple to program and easily applied to non-homogenous refractive index profiles. This method subdivides the domain into many subregions, in which the partial derivatives are replaced by finite difference operators. A set of linear equations are then solved to obtain the eigenvalues. The drawback of the FDM is it offers less flexibility in the modeling of the domain since the subregion is normally rectangular in shape [6]. The waveguide cross section is divided into surface or volume elements and the field in each element is approximated by a polynomial. The field continuity conditions are imposed on all interfaces between the different elements. A variational expression for Maxwell's equations then is employed to obtain an eigenvalue matrix equation which is solved by standard methods. This method requires a more complex

Received November 14, 2016; Revised January 30, 2018; Accepted April 16, 2018

4 TELKOMNIKA

programming structure and is more demanding in both computer time and memory [7]. The beam propagation method (BPM) has been used to analyze various two- and three-dimensional optical device 10 he original BPM used an FFT algorithm and solved a paraxial scalar wave equation. The basic idea of the BPM is to represent the electromagnetic field by a superposition of plane waves propagating in homogenous media. The advantages of the BPM are that it can be applied to a structure with an arbitrary cross-section, and that both guided and radiative waves are included in the analysis. However since the formulation is derived under the 36 umption that the refractive index variation in the transverse direction is very small, the FFT-BPM cannot be applied to structure 23 th large index discontinuities [6].

The method of lines (MoL) has been proved to be a very useful tool for the analysis of general waveguide systems [8]. It is a semi analytical method, in which the wave equation is discretized as far as necessary in the transverse direction and solved analytically in the longitudinal direction, which results in less computational effort. An accurate result can be obtained since the moL behaves in a stationary fashion and convergence is monotonic [9]. Discontinuous fields can be described accurately because the interface conditions are included in the calculation. Furthermore, the MoL is relatively easy to implement using computer numerical methods. In this paper we compare two different approaches, namely a simple quasianalytic theory based on integeo of a phenomenological absorption coefficient, and the method of lines (MoL). Both are applied 9 a number of different waveguide bend curvatures.

In this paper we applied the method of lines with third order absorbing boundary condition to analyse weakly guiding optical waveguides bends characteristics. For the first approximation we have transformed the Helmholtz wave equation in polar co-ordinates to Cartesian coordinates to simplify the discretisation of waveguide structures. In the process we compared the results with analytical methods as the correct references that has been developed previously. We found that the MoL results are in good agreement with analytical methods. The discrepencies arised from differents radius of curvature used in the calculation and the choices of absorbing boundaries parameters.

2. Research Method

2.1. Analytical Approach

To analyse the effect of a waveguide b(32), consider a bend formed by a circular arc with radius of curvature *r* as shown in Figure 1. It is assumed that only the fundamental mode propagates in the guide. If the radius of curvature is large enough ($r \rightarrow \infty$), then the properties of the mode are effectively those of a mode traveling in a straight guide. However, as *r* decreases, attenuation is expected to occur. Let *P*(*s*) be the total power carried by the mode at any point *s* along the bend. Assuming that the rate of power loss is proportional to the power carried by the mode at that point, we can write:



Figure 1. Section of a curved planar waveguide

$$\frac{dP(s)}{ds} = -\alpha P(s)$$

(1)

Modelling Optical Waveguide Bends by the Method of Lines (Ary Syahriar)

ISSN: 1693-6930

where α is the attenuation coefficient. Provided α is constant, equation 1 has the solution:

$$P(s) = P(0)e^{-\alpha s} \tag{2}$$

Marcatili and Miller have shown that the attenuation coefficient is indeed constant for a fixed radius, and can be expressed as [10]:

$$\alpha = C_1 e^{-C_2 r} \tag{3}$$

where C_1 and C_2 are functions of the waveguide parameters but are independent of *r*. Equation 3 shows that the attenuation coefficient increases exponentially with decreasing bending radius; however, if the radius of curvature become large enough the attenuation becomes negligible. It also shows that the change of α with *r* is dominated by the value of C_2 , which (for a weakly-guiding guide) is given by [11]:

$$C_2 = \frac{2\pi \left(2\Delta n_{eff}\right)^{\frac{3}{2}}}{\lambda \sqrt{n_2}} \tag{4}$$

Here $\Delta n_{\text{eff}} = n_{\text{eff}} - n_2$, where n_2 is the refractive index of the cladding.

The C_2 value also provides a method for characterising mode confinement, which is useful when investigating techniques for reducing bend losses. Equation 3 shows that α is also affected (but less strongly) by the value of the coefficient C_1 , which is defined as [11]:

$$C_1 = \frac{1}{2Z_c} \frac{\chi_1'}{\chi_1}$$
(5)

where the parameters Z_c , χ_t , and χ_l are given by:

$$Z_{c} = \frac{n_{2}}{2\lambda} \left[h + 2\sigma \cos(\frac{\kappa h}{2}) \right]^{2}$$
(6)

$$\chi_t = \frac{h}{2} + \frac{1}{2\kappa} \sin(\kappa h) + \sigma \cos^2(\frac{\kappa h}{2})$$
(7)

and,

$$\chi_{I} = \frac{\sigma}{2} \cos^{2} \left[\frac{\kappa h}{2} \right] e^{\frac{h}{\sigma}}$$
(8)

where σ is given by:

$$\frac{1}{\sigma} = \sqrt{\beta^2 - k_0 n_2^2} \tag{9}$$

and *h*, γ and κ have their usual meanings [12].

22 ne C_1 coefficient as defined in equation 4 is not a direct function of Δn_{eff} , but is related to the difference between the propagation constant within the guide and the cladding refractive index n_2 . Additionally, the C_1 coefficient is strongly model dependent, and so can be used to calculate the guide shape and other parameters. The above formulation of the C_1 and the C_2 coefficients was based on the derivation made by Marcatili et.al [10] and later adopted by Minford et.al [11]. However, two other formulations have been provided by Lee [12] and Marcuse [13,14]. Lee's version of the C_1 and the C_2 coefficients is as follows [12]:

TELKOMNIKA Vol. 16, No. 4, August 2018: 1490-1499

1492 🔳

TELKOMNIKA ISSN: 1693-6930 1493

$$C_{1} = \frac{2\gamma^{2}}{k_{o}n_{2}(\gamma h + 2)} \cos^{2}(\frac{\kappa h}{2})e^{\gamma h}$$
(10)

and,

$$C_2 = \frac{2\gamma(n_{eff} - n_2)}{n_2}$$
(11)

Here, k_{0} , κ , γ , and h have their usual meaning. In a similar way, Marcuse's version of the coefficients is as follows [14]:

$$C_{1} = \frac{2\gamma^{2}}{\beta(2+\gamma\hbar)(n_{1}^{2} - n_{2}^{2})k_{o}^{2}}\exp(\gamma\hbar)$$
(12)

and,

$$C_2 = \frac{2}{3} \frac{\gamma^3}{\beta^2}$$
(13)

here, the propagation constant is defined as $\beta = k_o n_{eff}$. It might be expected that these different formulations would give similar results; however, this was not found to be the case.

2.2. Method of Lines

In this analysis we begin by considering the behaviour of a guided mode as it travels a bend of constant curvature. Figure 2 shows a schematic of the geometry. The waveguide has a constant radius of curvature r, which is measured from the centre of the guide. The guide is of width h, which is as 21 med to be much less than r and is centred on a computational window of width w. The core and cladding refractive indices are given by n_1 and n_2 respectively.



Figure 2. Discretisation of a planar waveguides bends by the MoL

Assuming a *y*-polarised electric field, the Helmholtz wave equation can be written in polar co-ordinates as [15]:

Modelling Optical Waveguide Bends by the Method of Lines (Ary Syahriar)

ISSN: 1693-6930

$$\frac{1}{\rho}\frac{\partial E_y}{\partial \rho} + \frac{\partial^2 E_y}{\partial \rho^2} + \frac{1}{\rho^2}\frac{\partial^2 E_y}{\partial \varphi^2} + k_o^2 n^2 E_y = 0$$
(14)

To implement a numerical solution of equation 14 a modification must be made. It involves changing the co-ordinates to a local co-ordinate system that follows the centre of the waveguide along the propagation direction [15]. This change also allows the possibility of analysing the field profile at the local cross-section. By making the substitution:

$$\rho = x + r$$

$$s = r\varphi$$
(15)

Equation 14 may be transformed to:

$$\frac{\partial^2 E_y}{\partial x^2} + (1+cx)^2 \frac{\partial^2 E_y}{\partial x^2} + c(1+cx) \frac{\partial E_y}{\partial x} + (1+cx)^2 k_0^2 n^2(x) E_y = 0$$
(16)

where the constant c = 1/r represents the waveguide curvature. Note that it is easy to see how equation 16 reduces to the scalar wave equation for a straight waveguide when c=0. There are some advantages using equation 16. Firstly, the computational window can be restricted because the centre is along the path of the waveguide. Secondly, the index profiles need not be altered as the radius of curvature changes, in contrast to the other methods which use the modified index profile [15]. To solve equation 16 by the MoL, the equation is now discretised using the finite difference operator, by putting:

$$\frac{\partial^2 E_y}{\partial x^2} \approx \frac{E_{i+1} - 2E_i + E_{i-1}}{\left(\Delta x\right)^2} \tag{17}$$

and:

$$\frac{\partial E_y}{\partial x} \approx \frac{E_{i+1} - E_{i-1}}{2\Delta x}$$
(18)

If this is done, equation 16 can be written in matrix form as:

$$\frac{d^2\vec{E}}{ds^2} + \vec{Q}\vec{E} = 0 \tag{19}$$

where $E = [E_1, E_2, E_3, \dots, E_N]^{t}$ is a column vector containing discretised values of the field $E_y(x)$, at the points x_1, x_2, \dots, x_N , and \vec{Q} is a tri-diagonal matrix defined by :

TELKOMNIKA Vol. 16, No. 4, August 2018: 1490-1499

1494 🔳

TELKOMNIKA

ISSN: 1693-6930

1495

Assuming that there is no back-reflection, the general solution for constant matrix elements has the form:

$$\vec{E} = \vec{T}e^{-j\vec{\beta}s}\vec{T}^{-1}\vec{E}_{inp}$$

(21)

where \vec{T} is a matrix containing the eigenvectors of \vec{Q} arranged in columns, $\vec{\beta}$ is a diagonal matrix containing the eigenvalues of \vec{Q} , and \vec{E}_{imp} is the input field vector. One of the most important parameters associated with the waveguide is the fractional power that remains in the core at point *z*. This power is approximately given by the overlap integral:

$$\frac{25}{P(z)} = \left| \int_{-\infty}^{\infty} E(x,0)E(x,z)dx \right|^2$$
(22)

where E(x,0) is the input field and E(x,z) is the field at point z.

19 2.3. The Absorbing Boundary Condition

To calculate the modal field of the curved waveguide, it is necessary to restrict the extent of the computational window. Once again, this is done using absorbing boundary conditions. Derivation of appropriate boundary conditions in polar co-ordinate is generally rather complicated [16]. In the calculation described here, we have adopted a simpler approate applying a straight guide boundary condition to the curved waveguide equation 5 y using the assumption that the radius of curvature is large enough that the mode inside the bend is similar to that of straight guide.

The absorbing boundary condition is inserted into the edge of the matrix components of equation 20 [16]. In this case, we have used the more effective third-order absorbing boundary condition, where the radical is approximated by:

$$\sqrt{1+S^2} \approx \frac{p_0 + p_2 S^2}{q_0 + q_2 S^2}$$
(23)

Differences in the choice of the coefficients, p and q, produces different families of absorbing boundary conditions. These result in differences in the angle of exact absorption of the incoming wave by the absorbing boundary layer. Table 1 shows a list of the coefficient values and absorption angles of the approximations that are most commonly used. Here, we have used the L_{∞} type of approximation.

Table 1. Coefficients fo	r different third-order	· absorbing	boundary	conditions.

	af	ter referenc	e [4.16]	
Type of approximation	p_0	p2	q_2	angle of exact absorption (°)
Pade'	1.0000	-0.7500	-0.2500	0.0
Chebyshev L^{∞}	0.9997	-0.8086	-0.3165	11.7, 31.9, 43.5
Chebyshev points	0.9965	-0.9129	-0.4725	15.0, 45.0, 75.0
Least square (L ₂)	0.9925	-0.9223	-0.5108	18.4, 51.3, 76.6
Chebyshev-Pade' (C-P)	0.9903	-0.9431	-0.5556	18.4, 53.1, 81.2
Newman points	1.0000	-1.0000	0.6697	0.0, 60.5, 90.0
Chebyshev L _∞	0.9565	-0.9435	0.7038	26.9, 66.6, 87.0

 $q_0 = 1.0000$ for each approximation

3. Results and Analysis

To get a better understanding on how the guided mode evolution during its propagation inside curved waveguides; we have used two methods, i.e. an analytical theory that is assumed to be the right approach and the method of lines. In both calculations parameters of a waveguide bends with a radius 5000 μ m through an angle of 45° with different refractive index

Modelling Optical Waveguide Bends by the Method of Lines (Ary Syahriar)

changes have some used. Figure 3 shows the variation of C_2 calculated using equation 4 with wavelength for different values of Δn , i.e. for different degrees of waveguide confinement. These results show that C_2 increases as the confinement becomes higher and also that C_2 values generally decrease slowly at long wavelengths.



Figure 3. Variation of the parameter C_2 with wavelength, for different values of Δn as predicted by equation 4

Figure 4 (a) and (b) show a comparison of the C_1 and the C_2 values as a function of waveguide width, calculated by Marcatili's approximation of equation 4 and 5; Lee's approximation of equation 10 and 11; and Marcuse's approximation of equation 12 and 13 respectively. Here, the parameters of n_1 =1.463, n_2 =1458, λ =1.525 µm, with h varying from 4 µm to 7 µm, have been used.



Figure 4. A comparison of different approximations for (a) the C_1 value, and (b) the C_2 value

Figure 4 (a) shows that the C_1 coefficients of Lee's and Marcuse's expression are in a good agreement. However, Marcatili's equation gives much lower value. This might well be because of the different epproaches used to derive the C_1 coefficient. The Marcatili approximation is obtained from the complex solution of the eigenvalue equation of the waveguide bend, while both Lee and Marcuse use a different approximation based on the local rate of power radiation from the bend. Furthermore, for the C_2 coefficient, Lee's and Marcatili's approximations give a good agreement, while Marcuse's approach gives apparently incorrect values. It can be concluded that Lee's expression is the most likely to be correct. This assumption will be validated later by comparison with the rigorous method of lines.

TELKOMNIKA Vol. 16, No. 4, August 2018: 1490-1499

TELKOMNIKA

ISSN: 1693-6930

To illustrate the way in which the guided mode evolves in a curved waveguide, we first compare the input and output mode shapes obtained after travelling round a bend of radius 5000 μ m through an angle of 45°. Figure 5 (a) shows results obtained for a guide of core index 1.464, cladding index 1.458 and width 5 μ m at a wavelength of 1.525 μ m, while Figure 5 (b) shows results for a similar but less strongly confining guide which has a core index of 1.463. The calculations have been done by using the MOL scheme.



Figure 5. Input and output field distribution of the fundamental mode after travelling around a waveguide bend of radius 5000 μ m through an angle of 45⁰. (a) $\Delta n = 0.006$, (b) $\Delta n = 0.005$

Figure 5 demonstrates that the output field profile of the mode generally extends into the cladding and its peak is reduced, so that it is gradually radiating power. The amount of the power loss depends on the degree of confinement. For example, in Figure 5(a), the output field extends into the cladding only to a very limited extent, and the input and the output field shapes are very similar. However, in Figure 5(b) the output field extends much further into the cladding due to the reduction in confinement. The degree of asymmetry also increases considerably as the confinement is reduced.

We now use the results of the method of lines calculation to estimate an effective attenuation coefficient along a uniformly curved waveguide. This can be done by using equation 1, where the $\frac{dP(s)}{r}$ values are found by evaluating the difference in the integrated 5

ds

optical power across the mode in the computational area between two adjacent axial propagation steps. Figure 6 shows the attenuation coefficient found in this way as a function of bending angle φ , for the parameters Δn =0.005, 0.006, and 0.007, n_2 =1.458, λ =1.525 μm , h=5 µm, and r=5000 µm.

Modelling Optical Waveguide Bends by the Method of Lines (Ary Syahriar)



Figure 6. Attenuation coefficient as a function of the bending angle φ , for a different degrees of confinement

In each case, the value of α is not constant, but rises gradually from zero at the start of the bend and settles to a steady-state value only after some rapid fluctuations. In early analyses, the fluctuations have been associated with transition loss [17-18]. However, recently it was demonstrated that they are merely a mathematical artefact which is inherent in numerical modelling of bends using beam propagation methods, and the steady-state value is an accurate estimate of the attenuation coefficient after the mode has settled to its final lateral position.

A comparison of the attenuation coefficients predicted by simple theory and the MoL (at large axial distance) is shown in Figure 8. In the analytical approximations, the C_1 and the C_2 coefficients needed to find the α values have been calculated by using each of the three approximations.





Figure 8 demonstrates that good agreement is obtained between the analytical form for the loss coefficient based on Lee's expression and the MoL calculation. A slight difference, however, occurs at a small radius. In contrast, Marcatili's formulation predicts a very low value of α when compared to Lee's approximation and the MoL calculation, while Marcuse's formulation predicts much higher values.

The residual discrepancies between the predictions of Lee's theory and the MoL may be explained as follows. In the MoL, the calculation results are highly dependent on a proper choice of absorbing boundary condition at the edge of the computational windows, so that unsuitable conditions give rise to significant reflection back into the computational window and hence lower apparent loss. A similar effect also appears in another numerical scheme [19].

TELKOMNIKA Vol. 16, No. 4, August 2018: 1490-1499

1498 🔳

TELKOMNIKA

ISSN: 1693-6930

4. Conclusion

We have investigated different analytic approximations to the local loss coefficient in waveguide bends based on constant radius of curvature, and have uncovered disagreement between several previously published analytical expressions. To verify the accuracy is the attenuation coefficient on several publish analytical expression, we have used the beam propagation algorithm based on the method of lines in polar co-ordinate. We have found reasonable agreement with the analytic approximation to the local loss coefficient based on Lee's approach. This agreement might be used to extend the calculation of loss in waveguide bends structure in modelling continuously-varying S-bends waveguides using cascaded structure of the absorbing boundary conditions used to limit the range of the calculation window.

References

- BE Little, ST Chu, HA Haus, J Foresi, JP Laine. Microring resonator channel dropping filters. J. Lightwave Technol. 1997; 15: 998-1005.
- [2] M Zirngibl, CH Joyner, LW Stulz, T Gaiffe, C Dragone. Polarization independent 8 × 8 waveguide grating multiplexers on In P. *Electron. Lett.* 1993; 29: 201-202.
- [3] RR Hayes, D Yap. GaAs spiral optical waveguides for delay-line applications. J. Lightwave Technol. 1993; 11: 523-528.
- [4] X Jiang, W Qi, H Zhang, Y Tang, Y Hao, J Yang, M Wang. Loss crosstalk 1 × 2 thermooptic digital optical switch with integrated S-bend attenuator. *IEEE Photon. Technol. Lett.* 2006; 18: 610-612.
- [5] F Ladouceur, JD Love. Silica-based buried channel waveguides and devices. Chapman & Hall. London. 1996.
- [6] WP Huang. Methods for modeling and simulation of guided-wave optoelectronic devices: part I: modes and couplings. EMW Publishing, Cambridge, Massachusetts, 1995.
- [7] SM Saad. Review of numerical methods for the analysis of arbitrarily-shaped microwave and optical dielectric waveguides. *IEEE Trans. on Microwave Theory and Tech.* 1985; MTT-33: 894-899.
- [8] T Itoh. Numerical techniques for microwave and millimeter-wave passive structures. John Wiley & Sons. New York. 1989.
- U Rogge, R Pregla. Method of lines for the analysis of dielectric waveguides. *IEEE J.Lightwave Technol.* 1993; LT-11: 2015-2020.
- [10] EAJ Marcatili. Bends in optical dielectric guides. Bell Syst. Tech. J. 1969; 48: 2103-2132.
- [11] WJ Minford, SK Korotky, RD Alferness. Low-loss Ti:LiNbO₃ waveguide bends at =1.3 m. IEEE J. Quantum Electron. 1982; QE-18: 1802-1806.
- [12] DL Lee. Electromagnetic principles of integrated optics. John Wiley & sons. New York. 1986.
- [13] D Marcuse. Length optimisation of an S-shaped transition between offset optical waveguides. Appl. Opt. 1978; 17: 763-768.
- [14] D Marcuse. Bending losses of the asymmetric slab waveguide. Bell Syst. Tech. J. 1971; 50: 2551-2563.
- [15] SJ Garth. Mode behaviour on bent planar dielectric waveguides. IEE Proc. Optoelectron. 1995; 142: 115-120.
- [16] TG Moore, JG Blaschak, A Taflove, GA Kriegsmann. Theory and application of radiation boundary operators. *IEEE Trans. Antenna and Prop.* 1988; 36: 1797-1812.
- [17] J Yamauchi, S Kikuchi, T Hirooka, M Nakano. Beam propagation analysis of bent step-index slab waveguide. *Elect. Lett.* 1990; 26: 822-824.
- [18] M Rivera. Lowest-order mode transmission in multimode dielectric S-bends. Opt. Quantum Electron. 1997; 29: 323-333.
- [19] J Saijonmaa, D Yevick. Beam-propagation analysis of loss in bent optical waveguides and fibers. J. Opt. Soc. Amer. 1983; 73: 1785-1791.

Modelling Optical Waveguide Bends by the Method of Lines (Ary Syahriar)

Modelling Optical Waveguide Bends by the Method of Lines

ORIGIN	IALITY REPORT				
SIMIL	5% ARITY INDEX	5% INTERNET SOURCES	10% PUBLICATIONS	4% STUDENT P	APERS
PRIMA	RY SOURCES				
1	Submitte Student Paper	d to Universiti Ma	alaysia Perlis		2%
2	journal.u	ad.ac.id			1%
3	Vivek Sir characte core with cross see Technolo Publication	ngh. "Weak guida ristics of an optic a sinusoidally va ction", Microwave ogy Letters, 07/20	ance modal dis al waveguide l arying gear-sha e and Optical 0/1999	persion having a aped	1%
4	Submitte Student Paper	d to Universitas	Brawijaya		1%
5	Yamauch Nakano. step-inde Letters, 7 Publication	ni, J., S. Kikuchi, "Beam-propagat ex slab waveguid 1990.	T. Hirooka, an ion analysis of es", Electronic	d H. ⁵ bent s	1%
6	R. Pregla	a. "The method o	f lines for the a	analysis	1 ~

of dielectric waveguide bends", Journal of Lightwave Technology, 1996

Ŭ

∎ %

7	Kremer, Dennis, Reinhold Pregla, and Mario N. Armenise. "", Integrated Optics Devices Potential for Commercialization, 1997. Publication	1%
8	B. M. A. Rahman. "Numerical analysis of bent waveguides: bending loss, transmission loss, mode coupling, and polarization coupling", Applied Optics, 06/01/2008 Publication	1%
9	www.fernuni-hagen.de	<1%
10	Submitted to University of Glasgow Student Paper	<1%
11	H.A. Jamid, M.N. Akram. "A new higher order finite-difference approximation scheme for the method of lines", Journal of Lightwave Technology, 2001 Publication	<1%
12	hdl.handle.net Internet Source	<1%
13	Madsen. "Fundamentals of Electromagnetic Waves and Waveguides", Wiley Series in Microwave and Optical Engineering, 06/01/1999 Publication	<1%

Jeffrey G Blaschak, Gregory A Kriegsmann. "A

14	comparative study of absorbing boundary conditions", Journal of Computational Physics, 1988 Publication	<1%
15	M. Rivera. "A finite difference BPM analysis of bent dielectric waveguides", Journal of Lightwave Technology, 1995 Publication	< 1 %
16	Won Jay Song. "Scalar BPM analyses of TE and TM polarized fields in bent waveguides", IEEE Transactions on Antennas and Propagation, 6/2003 Publication	< 1 %
17	eprints.utm.my Internet Source	<1%
17	eprints.utm.my Internet Source T. Kitoh, N. Takato, M. Yasu, M. Kawachi. "Bending loss reduction in silica-based waveguides by using lateral offsets", Journal of Lightwave Technology, 1995 Publication	<1%

Jalal Nazarzadeh, Hamidreza Radmanesh.

20	"Hybrid extended Fourier series for optimal control of nonlinear algebraic dynamical systems", Journal of Control Theory and Applications, 2011 Publication	<1%
21	Rowland, D "Nonperturbative calculation of bend loss for a pulse in a bent planar waveguide", IEE Proceedings - Optoelectronics, 1997. Publication	<1%
22	W.J. Minford, S.K. Korotky, R.C. Alferness. "Low-Loss Ti: LiNbO/sub 3/ Waveguide Bends at Lambda = $1.3 \mu m$ ", IEEE Transactions on Microwave Theory and Techniques, 1982 Publication	< 1 %
23	epubs.surrey.ac.uk Internet Source	<1%
24	www.matec-conferences.org	<1%
25	media.neliti.com	<1%
26	proxy.osapublishing.org	<1%

the method of lines", Journal of Lightwave

Technology, 1999 Publication

28

Muttukrishnan Rajarajan. "Design of Compact Optical Bends with a Trench by use of Finite-Element and Beam-Propagation Methods", Applied Optics, 09/20/2000

<1%

<1%

Publication

- D. Marcuse. "Bend loss of slab and fiber modes <1% 29 computed with diffraction theory", IEEE Journal of Quantum Electronics, 1993 Publication
- B. Stupfel. "A fast-domain decomposition <1% 30 method for the solution of electromagnetic scattering by large objects", IEEE Transactions on Antennas and Propagation, 1996 Publication

31	portal.research.lu.se	<1%

32

pt.scribd.com

Internet Source

<**1**% Devayani, Indah Juningtiaz, Ary Syahriar, and 33 Dwi Astharini. "Characteristics of S-bend optical waveguides based on back-to-back and sinusoidal structures", 2014 International Conference on Electrical Engineering and Computer Science (ICEECS), 2014. Publication



nternet Sourc

<**1**%



34

Fakhrurrozi, Subekti Ari Santoso, S Octarina Nur, Ary Syahriar. "Temperature effects on parallel cascaded silica based microring resonator", 2013 International Conference of Information and Communication Technology (ICoICT), 2013 Publication <1%

Ping-Lin Fan, Mount-Learn Wu, Ching-Ting Lee.
"Analysis of abrupt bent waveguides by the beam propagation method and the conformal mapping method", Journal of Lightwave
Technology, 1997
Publication



36

P.D. Sewell, T.M. Benson. "Efficient curvature analysis of buried waveguides", Journal of Lightwave Technology, 2000

<1%

<1%

On

Exclude matches

Off

Exclude bibliography On

On Mon, Nov 14, 2016 at 3:49 PM, Tole Sutikno <tole@journal.uad.ac.id> wrote:

Dr. Ary - Syahriar:

Thank you for submitting the manuscript, "Modelling Optical Waveguide Bends by the Method of Lines" to TELKOMNIKA (Telecommunication Computing Electronics and Control). With the online journal management system that we are using, you will be able to track its progress through the editorial process by logging in to the journal web site:

Manuscript URL:

http://journal.uad.ac.id/index.php/TELKOMNIKA/author/submission/5191 Username: ary

If you have any questions, please contact me. Thank you for considering this journal as a venue for your work.

Tole Sutikno TELKOMNIKA (Telecommunication Computing Electronics and Control)

Dear Dr. Ary - Syahriar,

It is my great pleasure to inform you that your paper has been **accepted** and will be published on the TELKOMNIKA Telecommunication Computing Electronics and Control (ISSN 1693-6930, SCOPUS indexed journal). **Congratulations!**

Please prepare your final paper adheres every detail of the guide of authors, and check it for spelling/grammatical mistakes.

In order to cover part of the publication cost, each accepted paper will be charged:

Publication Fee: USD 265 (or IDR 3,000K for Indonesian Authors)

This charge is for the first 8 pages, and if any published manuscript over 8 pages will incur extra charges USD 50 (or IDR 500K for Indonesian Authors) per page

The payment should be made by bank transfer (T/T):

Bank Account name (please be exact)/Beneficiary: ANTON YUDHANA

Bank Name: Bank Central Asia (BCA)

Branch Office: Kusumanegara

City: Yogyakarta

.

Country : Indonesia

Bank Account # : 8465023984

SWIFT Code: CENAIDJAXXX

Cell. Phone: +6285746722592

or through PayPal (as alternative of bank transfer) to email: tole@ee.uad.ac.id

Your paper will be scheduled for forthcoming issue. Please pay the publication fee as soon as possible (within 3 weeks). If you need more time, please send a request to this email. We can give you 5 weeks at the most.

Then, please submit your final paper & payment receipt to this email

I look forward for your response

Sincerely yours,

Tole Sutikno

Editor-in-Chief, TELKOMNIKA

Please ensure that all references have been cited in your text; Each citation should be written in the order of appearance in the text; The references must be presented in numbering. The references must be integrated also with not less than two papers published on 2015-2017 issues:

- IAES Journals, You can find the references at: http://iaescore.com/journals - TELKOMNIKA TCEC at http://journal.uad.ac.id/index.php/TELKOMNIKA

- Indonesian Journals at http://journal.portalgaruda.org/index.php/eei

*

- IAES Section Journals at http://section.iaesonline.com/index.php/ijeei

Please prepare your revised paper perfectly adhere the guide of authors. Please get take a look at:http://goo.gl/FiPFbF