IEEE CITISIA 2021



IEEE Conference on Innovative Technologies in Intelligent System & Industrial Application

CONFERENCE PROCEEDINGS

24-26 November 2021 Sydney, Australia

Conference Committee for CITISIA 2021

Main Committee

Chandana Withana – Co-Chair Charles Sturt University, Australia Simi Bajaj – Co- Chair Western Sydney University, Australia SMN Arosha Senanayake – Co-Chair Universiti Brunei Darussalam Abeer Alsadoon – Technical Chair Charles Sturt University, Australia Angelika Maag – Publication Chair Western Sydney University, Australia Parkat Neupane – Secretary Charles Sturt University, Australia Jinfeng Su – Account support Charles Sturt University, Australia

Program Committee

Abeer Alsadoon – Chair Charles Sturt University, Australia Anchal Kumar Shrestha – Member Charles Sturt University, Australia Binod Syangtan – Member Charles Sturt University, Australia Indra Sehar – Member Charles Sturt University, Australia

Publication Committee

Angelika Maag – Chair Western Sydney University, Australia Ammara Khan – Member Charles Sturt University, Australia Ahmed Dawoud – Member Charles Sturt University, Australia Antoinette Cevenini – Member Western Sydney University, Australia Daniel Saffioti – Member Western Sydney University, Australia Fatima Furqan – Member University of Technology Sydney, Australia George Zajko – Member University of Canberra, Australia, Australia Jonathan Lavaro – Member Charles Sturt University, Australia Linh Pham – Member Western Sydney University, Australia Mahsa Razavi – Member Western Sydney University, Australia Mohammad Momani – Member Charles Sturt University Nabil Giweli – Member Charles Sturt University, Australia Nectar Costadopoulos - Member Charles Sturt University Ross Gunasekara – Member Charles Sturt University Thair Attallah Ilyas Al-Dala'in - Member Charles Sturt University, Australia Yahini Murugesan – Member Charles Sturt University, Australia

Website and Social Media

Surendra Khattri – Chair *Charles Sturt University IEEE Student Branch* Binod Syangtan – Advisor *Charles Sturt University IEEE Student Branch* Manas Saha – Member *Charles Sturt University IEEE Student Branch* Prakriti Upadhyay Wagle – Member *Charles Sturt University IEEE Student Branch* Mahendra subedi – Member *Charles Sturt University IEEE Student Branch*

Table of Content

All Rights Reserved	viii
Welcome Message from the Founder of CITISIA	ix
Conference Committees	X
International Advisory Committee	xi
IEEE CSU Student Branch	xii

[2] Data security and privacy in cloud computing focused on the transportation sector with the aid of blockchair
approach(1
Abhiyan Gurung

[3] The Implementation of Low RPM Generator on Small Scale Savonius Vertical Axis Wind Turbine (VAWT)(10)
Fahmi Adam Augusta, Ary Syahriar, Ahmad Husin Lubis and Putri Wulanda
[4] Early Detection of Under-Performing Students Using Machine Learning Algorithms(15)
Khalid Alalawi, Raymond Chiong and Rukshan Athauda
[5] Identifying Parkinson's Disease using Multimodal Approach and Deep Learning(23)
Mahsa Mohaghegh and Jaya Gascon
[6] Lazy Susan Calorie Monitoring Dining Table Based on Raspberry Pi(29)
Tonny Kurniawan, Hervinsen Zhang, Rico Wijaya, Jimmy Linggarjati, Savita Sondhi and Rinda Hedwig*
[7] DCV: A Taxonomy on Deep Learning Based Lung Cancer(36)
SubodhTiwari, Salma Hameedi Abdullah, Rashidul Mubasher, Abeer Alsadoon and P.W.C. Prasad
[9] Utilizing Blockchain to Enhance the Privacy and Block Validity in Healthcare Systems(46)
Sonia Devi, Abeer Alsadoon, Sreekanth Gopalakrishnan Nair, Ahmed Dawoud, Oday D. Al-Jerew, Benoy
Varghese and P.W.C. Prasad
[10] Computing Infrastructure Of IoT Applications In Smart Agriculture: A Systematical Review(55)
Mai Ha Thi 1, Le Hoang Son 2, Nguyen Tran Quoc Vinh 1, Nguyen Thi Huong Quynh 3

[11] Qos based Security Architecture for Software-Defined Wireless Sensor Networking(64)

Himanshi Babbar, Shalli Rani, Sardar M N Islam and Sailesh Iyer

[15] Towards Business Process Intelligence to Port2Port Governance Responsibility based on Learning Algorithms
A.X. Halabi-Echeverry, Juan C. Aldana-Bernal, Diego Villate-Daza and Sardar M. N. Islam
[19] An Innovative Framework to Improve Course and Student Outcomes(73)
Khalid Alalawi, Rukshan Athauda and Raymond Chiong
[21] Generating Product Description with Generative Pre-trained Transformer 2(78)
Minh-Thuan Nguyen, Phuong-Thai Nguyen, Van-Vinh Nguyen and Quang-Minh Nguyen
[24] Threats and data trading detection methods in the dark web
Junyan Li
[25] A Heuristic Approach using Block Chain to Fight Novel COVID-19 During an Election(94)
Ira Nath, Pratnadeep Biswas, Kankana Ganguly, Dharmpal Singh, Sardar M.N. Islam, Ton Quang Cuong and Souvik Pal
[26] Prediction of Forest Fire Using Machine Learning Algorithms: The Search for the Better Algorithm(100)
Pranati Rakshit, Srestha Sarkar, Sambit Khan, Pritam Saha, Sonali Bhattacharyya, Nilarpan Dey, Sardar M.N. Islam and Souvik Pal
[28] DNA based service data security in cloud computing environment(106)
Amisha Patel, Zhongyan Ge, Indra Seher and Van Luong Vo
[29] Predicting Hypoglycaemia Using Classification(116)
Neelam Maharjan, Binod Syangtan, Amr Alchouemi and Moshiur Bhuiyan
[33] Design Analysis of HPF and LPF with Bode Plotter in Multisim
Dary Zhafran and Putri Wulandari
[35] Improving Weeds Identification with a Repository of Agricultural Pre-trained Deep Neural Networks(133)
Rekha Sharma, A B M Mehedi Hasan, Jinfeng Su and Moshiur Bhuiyan
[36] Enhancing the security of data in cloud computing environments using Remote Data Auditing(142)
Muhammad Akmal, Binod Syangtan and Amr Alchouemi
[37] Topic: Scoping review of Blockchain-based data storage technique in industrial IoT data management(152)
Aanchal, A. and Prasad, P.W.C.
[38] Customer data extraction techniques based on natural language processing for e-commerce business analytics

Abdul B. Maqsood1, Angelika Maag, Indra Seher and Md Sayfullah

[39] A review of Blockchain-based batch authentication techniques for securing the Internet of Vehicles(170)
Aqeel Mustafa1, Binod Syangtan1, Angelika Maag2, Amr Elchouemi3
[40] Using Deep learning for network traffic prediction to secure Software networks against DDoS attacks(180)
Tulasi Sulaga, Angelika Maag, Indra Seher and Amr Elchouemi
[41] Ledger Technology of Blockchain and its Impact on Operational Performance of Banks: A Review(190)
Teja Goud Allam, A B M Mehedi Hasan, Angelika Maag and P.W.C. Prasad
[57] Data Aggregation Techniques in Wireless Sensors Networks: A survey(200)
Syed Sikandar Ali, Nabil Giweli, Ahmed Dawoud and P.W.C. Prasad
[58] Data Aggregation Techniques in Wireless Sensors Networks: A survey(210)
Syed Sikandar Aliı, Nabil Giweli2, Ahmed Dawoud2, P.W.C. Prasad2
[59] A Review on Wireless Telemedicine Technology Challenges and Possible Solution(219)
Bishwajeet Roy, P.W.C. Prasad and Angelika Maag
[60] An Approach For Improving Transparency And Traceability of Industrial Supply Chain With Blockchain Technology
Aman Kaushik and Nitin Jain
[63] Review of existing variants of Grey Wolf Optimization algorithm handling Load Balancing in Clouds .(233)
Suman Sansanwal and Nitin Jain
[66] A Sentiment Analysis of Amazon Review Data Using Machine Learning Model(239)
Rajat, Priyanka Jaroli, Naveen Kumar and Rajesh Kumar Kaushal
[68] Development Approaches To Intuitive, SSD & Haptics Integrated HRI & Social HRI systems for Assisting Space Exploration(245)
Aman Arora, S.N. Panda, Jagdish Raheja and Dimple Nagpal
[70] Cloud-based big data analytics for improving the processing of customer's data in SME's (252)
Harshith Shrestha and Kavindie Senanayake
[72] Real-time supply chain tracing using blockchain from cloud-based computing portal(262)
Gowind Misra and Kamini Simi Bajaj
[73] Review of network-forensic analysis optimization using deep learning against attacks on IoT devices(271)
Samriddha Adikari, Jinfeng Su and Kamini Simi Bajaj

The Implementation of Low RPM Generator on Small Scale Savonius Vertical Axis Wind Turbine (VAWT)

1st Fahmi Adam Augusta Electrical Engineering Department Universitas Al-Azhar Indonesia South Jakarta, Indonesia fahmiadamaugusta@gmail.com

2nd Ary Syahriar Electrical Engineering Department Universitas Al-Azhar Indonesia South Jakarta, Indonesia ary@uai.ac.id

Abstract— Fossil energy, especially petroleum, is the main energy source and a source of foreign exchange. Indonesia has a limited amount of fossil energy. Meanwhile, energy consumption continues to increase along with the economic and population growth. Thus natural resources such as oil, gas, and coal are becoming more depleted, because they are not renewable energy. Indonesia is a tropical country located on the equator, as an archipelago with varied geological contours, more than 100 mountains, and also beaches. One of the energies that might be utilized is wind energy with an affordable cost and free pollutant output. Wind Turbines have become one of the feasible power plants to replace fossil energy. The mechanism of wind turbine is that the wind blows against the blades of the wind turbine, and allows the blades to rotate as the axis and produces a valuable source of renewable energy by repetitive rotational motion. This research was focused on finding a suitable generator for Savonius Vertical Axis Wind Turbine (VAWT) that can produce a high voltage at low RPM. In this research, to replicate the real wind blow, two different fans are used: a. 71 cm diameter industrial fan with range of wind speed from 1 to 6 m/s; b. 31 cm fan with a range of wind speed from 1 to 4,5 m/s. From the result, it can be concluded that the direction of the wind affects the rotation of the rotor, so it must be ensured that the wind touches the tip of the blade to maximize the rotational speed. The maximum voltage output produced by VAWT is 4,8 V at 67 RPM on wind speed 6 m/s using the 1st Generator. For further development, the Vertical Axis Wind Turbine (VAWT) have to be remodelled so the ratio between rotor radius and rotor height is 1.2.

Keywords—Vertical Axis Wind Turbine, Savonius, Low RPM Generator, Toll Road, Flow Simulation

I. INTRODUCTION

Fossil energy, especially petroleum, is the main energy source and a source of foreign exchange. Indonesia has a limited amount of fossil energy. Meanwhile, energy consumption continues to increase along with the rate of economic and population growth. Thus the natural energy resources are increasingly depleted. because most of the energy sources come from sources that are not renewable, such as oil, gas and coal [1].

Energy is a basic human need that must be fulfilled, it continues to increase as time passes, it is directly

3rd Ahmad Husin Lubis Electrical Engineering Department Universitas Al-Azhar Indonesia South Jakarta, Indonesia ahlubis@uai.ac.id

4th Putri Wulandari Electrical Engineering Department Universitas Al-Azhar Indonesia South Jakarta, Indonesia putri.wulandari@uai.ac.id

proportional to human life. Fuel oil holds a very dominant position in meeting national energy needs. The current composition of energy consumptions are fuel oil: 52,50%; gas: 19,04%; coal: 21,52%; water: 3,73%; geothermal: 3,01%; and renewable energy: 0,2% [2].

Indonesia is a tropical country located on the equator, as an archipelago with varied geological contours, more than 100 mountains, and also beaches. One of the energies that might be utilized is wind. The movement of wind from the mountains which has high air pressure towards the coast with low air pressure can be utilized in the implementation of wind turbines, which convert mechanical energy into electrical energy. Few advantages of this wind energy are inexpensive production cost, and free of pollutants [2].

Wind power is the future form of power generation. Basically, the kinetic energy of the wind is converted into mechanical energy for the production of electricity. The most common and familiar machine for generating wind power is the horizontal axis, which consists of a number of blades rotating around a central axis [3].

The blades of the wind turbine are driven by the wind, allowing the blades to rotate their axis, which is produced a very valuable source of renewable energy with repeated rotational motion. The wind turbine produces rotational motion, and the component which rotates to produce wind energy is called rotor. The conversion of wind energy into electrical energy is done by connecting a turbine to an electric generator [3].

An alternate form of producing wind energy, which is a modified version of the Horizontal Axis Wind Turbine (HAWT), is the Vertical Axis Wind Turbine (VAWT) model. An advantage of the VAWT model over its counterpart is that it operates independent of the direction of the wind. A key component of the Horizontal Axis Wind Turbine is that it requires a Yaw system. Yaw system is required in order to guide the turbine towards the direction of the wind, however this is not required for the vertical axis wind turbines. VAWT blades will rotate regardless of wind direction, this allows for cost efficiency during the manufacturing process. All Vertical Axis Wind Turbines are functioning by lift or drag principles [4].

This research has been conducted to demonstrate the efficiency and productivity of a VAWT, with a Savonius Rotor using 3 different kind of low RPM generator for producing voltage.

II. METHODOLOGY

This research was conducted following based on flow of research as illustrated in Figure II.1.



Fig. II.1 Flow of research

Figure II.1 demonstrates the Flow of Research. First, a review of various literatures as a reference for conducting this research is carried out. Then the wind speed measurement was carried out on the Tanjung Priok Toll Road as a reference for wind speed in the field. After that, 3D modeling was carried out for digital analysis using wind flow simulation on Solidworks. If the modeling is in accordance with the real specifications of the VAWT, Then proceed with the implementation of 3 generators on the VAWT. Then, the output power is calculated at the wind speed data that had been obtained using power equation. Then conclusions can be drawn from the results of the analysis.

III. RESULT AND ANALYSIS

A. Wind Speed Sampling

The source of the wind data used in the calculations were the same as the actual wind data obtained using anemometer in Tanjung Priok Toll Road location as shown in Figure III.1.



Fig. III.1. Tanjung Priok Toll Road

The selection of the location was based on wind data from the Global Wind Atlas web based [5]. On the wind speed map in North Jakarta [5], it can be seen that the North Jakarta was potential to get higher wind speed, especially Tanjung Priok. Figure III.2 shows the wind speed data sample for 3 days in a row.



Fig. III.2 Wind speed sample on Tanjung Priok Toll Road

From the wind speed data collection, it is known that the average of wind speed on Tanjung Priok Toll Road is 2,6 m/s and the maximum wind speed is 4,2 m/s.

B. Wind Flow Simulation



Fig. III.3. Determine the boundary conditions

Figure III.3 shows the condition of the wind direction and the environmental pressure of the wind tunnel. It can be seen if on the left, there is an arrow showing a red line to indicate the direction of the wind of 8 m/s which will move in the direction of the X axis.



Iteration = 63

Fig. III.4. Velocity contour in wind tunnel visualization (top view)

Figure III.4 shows the contour of the wind speed that rotates the wind turbine. It can be seen that the wind source moving from the left wall at a speed of 8 m/s, but approaching the wind turbine, the speed decreases to yellow, green to blue. This refers to Betz's Law, which states that wind turbines can only utilize 59,3% of the kinetic energy of the wind speed. More details can also be seen in Figure 4.8 where the contour is shown from the top side of the wind turbine. It can be seen clearly, on the advancing blade, the

wind speed is decrease to green contour, this means that the distance from the wind speed source can affect the wind speed received by the wind turbine blades. Figure III.5 shows how envircomental pressure affects the blade of the turbine.



Fig. III.5. Pressure Contour in wind tunnel visualization (top view)

The above simulation results will be used as a reference material for measuring voltage, RPM, and wind speed in the electrical laboratory. The distance between the wind source and the VAWT affects how much wind speed will be received by the turbine blades.

C. Small Scale VAWT Product

All VAWT specification data was taken from the existing Savonius VAWT model from latest project of Electrical Machinary Course on 2018 at the Indonesia Al-Azhar University [6-9]. The low RPM generator will be implemented on the base part of VAWT as shown in Figure III.6. This Table III.1 shows the detail of specifications of the VAWT.



Fig. III.6. Small Scale VAWT Product

Table III.1. Small Scale VAWT Dimension

VAWT Type	Savonius Vertical Axis Wind	
	Turbine (VAWT)	
Total Height (m)	1,81	
Base Height (m)	0,58	
Base Width (m)	0,60	
Blade Thickness (m)	0,008	
Rotor Length (m)	1	
Rotor Radius (m)	0,24	
Total Blade	3	
Blade Material	Stainless Steel	

From the generator implemented below, it can be seen the performance of the voltage output, RPM and wind speed from the existing VAWT.

D. Generator Implementation

Low RPM Generator was used as a converter of mechanical energy generated from the rotation of the turbine rotor into electrical energy. This wind turbine was driven by low wind speeds and the assumption that the rotational speed of the rotor was low. So, it needs a generator that could generate electricity at low rotations.



Fig. III.7. 1st Generator Implementation

The first generator implemented as shown in Figure III.7 is labeled as the 1^{st} generator and the specification for the 1^{st} generator is shown at Table III.2.

Table III.2 Specification of 1 st Generator		
1 st Generator Specifications		
Voltage	180	
Speed (R.P.M)	2400 +- 5%	
Frequency (Hz)	50/60 Hz	

Figure III.8 shows the implementation of the 2^{nd} and 3^{rd} generator with width of 150 mm and a height of 75 mm and the following at Table III.3 shows the specifications of the 2^{nd} and 3^{rd} generator.



Fig. III.8. 2nd and 3rd Generator Implementation

Table III.3 Low RPM Generator 12V and 24V Specification

Rated Voltage	12/24 V
Speed (R.P.M)	600 rpm
Maximum Resistance	0.5NM
Power Rating	400 W
Maximum Power	410 W
Control System	Electromagnetics

From Figure III.9, it can be stated that with low wind speeds $(1 \sim 4 \text{ m/s})$, the 3^{rd} generator has the highest voltage value. However, when the wind speed is more than 4 m/s, the output voltage value on 1^{st} generator is higher than 3^{rd} generator. While on 2^{nd} generator, the resulted

voltage is not greater than 1st and 3rd generator. The data obtained were consistent with the result obtained by Musawir stating that the greater the wind was obtained, the greater the voltage obtained [10].



Fig. III.9. Wind Speed vs Voltage for 3 Generators

But, before giving conclusions, it is necessary to know the RPM output values at the same wind speed condition. It can be seen that at the average wind speed in the field, namely, 2,6 m/s, the RPM values of the three generators namely from 1^{st} , 2^{nd} and 3^{rd} generator are 28, 69,1, and 80,1 respectively. An easier comparison of the RPM versus wind speed is shown in Figure III.10.



Fig. III.10 Wind Speed vs RPM for 3 Generators

One of the objective of this research was to find a suitable generator that can produce high voltage at low RPM. Figure III.10 shows that the one with lowest RPM is 1st generator, and in Figure III.9, the 1st generator also has a higher voltage.

The result was consistent with mathematical correlations in Eq (1) [11], showing that the wind speed increases with increasing the power output. Then, the correlations between Power to Voltage is linear. So the correlations between wind speed and voltage is linear.

$$P = VI = \frac{1}{2}\rho A v^3 \tag{1}$$

Where :

Р	= power generated from the savonius wind
	turbine (watts)
ρ	= wind density $(1,225 \text{ kg/m}^3)$
v	= wind speed (m/s)
A	= the swept area of the rotor (m^2)

The same phenomenon happens between the wind speed and RPM or ω , it shows in Eq (2) [12], when wind speed (v) is moved to the Tip Speed Ratio section, then the correlations between v and ω is linear.

$$TSR(\lambda) = \frac{\omega R}{n}$$
(2)

Where :

 $\begin{aligned} \lambda &= \text{Tip Speed Ratio} \\ \omega &= \text{Rotational Speed (RPM)} \\ \nu &= \text{Wind Speed (m/s)} \end{aligned}$

The recapitulation of generator implementation is shown at Table III.4

Table III.4 Implementation Recapitulation for 3 Generator

Parameter	G1	G2	G3
Voltage Output on	4 8 V	1 95 V	4 5 V
Wind Speed 6 m/s	4,0 V	1,95 V	ч,5 м
Voltage Output on			
Wind Speed Average	2,09	1,31	2,3
2.6 m/s			
RPM Output on Wind	28	60 1	80.1
Speed Average 2.6 m/s	20	09,1	00,1
Driven By 31 cm	VES	NO	NO
Diameter Fan	1123	NO	NO
Driven By 71 cm	VFS	VES	VFS
Diameter Fan	1125	1L5	1125
$V_{\text{desired}} = 13,7V$	182,7	685 rpm (not	342,5
	rpm	possible)	rpm

From the results of the implementation of the three generators above as shown at Table III.4, it is hereby decided that 1st generator has good performance on this Small Scale Vertical Axis Wind Turbine (VAWT). With the advantage that the shaft can rotate with a fan with a diameter of 31 cm, meaning that it can move at lower wind speeds. Considering that the implementation of this low RPM generator were not added by a voltage multiplier component such as a gearbox or step up transformer, it can be said that 1st generator is good enough to be implemented on this VAWT.

IV. CONCLUSION

From the research, resulting that the 1st generator produced higher voltage at low RPM than the other 2 generators. When the 1st generator is implemented, it can be turned using 31 diameter fan as a wind blow source. But it must be ensured that the wind touches the tip of the blade, positioning the wind direction also affects the rotational speed of the rotor. It is also known that VAWT needed larger force, wind speed, and pressure to be turned initially, if the wind speed is too low and does not collect at the tip point of the blade turbine, the turbine will not rotate.

REFERENCES

- Ramadhani, D. N. Design and simulation of vertical axis wind turbines with balance rotor blades 0021. Procedia of Engineering and Life Science Vol. 1 No.11 (1), 1–6. Sidoarjo, 2021.
- [2] Augusta, A, F., Al Afif, Wulandari, P., and Syahriar. A. *Vertical axis wind turbine analysis using MATLAB*. J. Phys. Conf. Ser., vol. 1517, no. 1, Jakarta, 2020.
- [3] Whittlesey, R. Vertical Axis Wind Turbines: Farm and Turbine Design In Wind Energy Engineering. pp 185-202. Elsevier Inc. United States. 2017.
- [4] Kim, M, G. Dalhoff, P, H. Yaw Systems for wind turbines Overview of concepts, current challenges and design methods Yaw Systems for wind turbines - Overview of concepts, current challenges and design methods. Department of Mechanical Engineering and Production Management. Hamburg, 2014.
- [5] "Global Wind Atlas". https://globalwindatlas.info/. 04/05/2021. 2021.
- [6] Al Afif, A., Wulandari, P., Syahriar, A. CFD analysis of vertical axis wind turbine using ansys fluent. J. Phys. Conf. Ser., vol. 1517, no. 1. 2020.
- [7] Isa, M., Syahbana, D., Pramana, A., Andika, R. Wulandari, P., Syahriar, A. Analysis Electricity System at Wind Power Plan (PLTB) Vertical. Jakarta. 2020.
- [8] Fajar, M, Al Afif, Idris A., Dhava, Adhytya, Wulandari, P., Syahriar, A. Charging and Discharging Battery System Automation in Simple Wind Power Plant. Research Gate. Jakarta. pp, 2. 2019.
- [9] Wasiati, S., Augusta, F., Purwanto, V., Wulandari, Putri., Syahrirar, A.. Darrieus type vertical axis wind turbine (VAWT) design. Journal of Physics: Conference Series. 1517. 012064. 10.1088/1742-6596/1517/1/012064. 2020.
- [10] Isa, M., Syahbana, D., Pramana, A., Andika, R. Wulandari, P., Syahriar, A. Analysis Electricity System at Wind Power Plan (PLTB) Vertical. Jakarta. 2020.
- [11] Jess. Wind Turbine Power Calculations. Mechanical and Electrical Engineering Power Industry. The Royal Academy of Engineering. Spain. 2003.

- [12] Kid Wind. Wind Energy Math Calculations: Calculating the Tip Speed Ratio of Your Wind Turbine. 1–5. 2015.
- [13] Y. K. Yadav, "A Savonius Wind Turbine with Electric Generator: Model and Test," *Grad. Sch. Clemson Univ.*, pp. 1–89. 2016.
- [14] Poultangari, I., Shahnazi, R., Sheikhan, M. RBF neural network based PI pitch controller for a class of 5-MW wind turbines using particle swarm optimization algorithm. ISA Transactions. Volume 51, Issue 5. Pages 641-648. 2012.
- [15] Shan. M., Jacobsen, S., Adelt, S., Field Testing and Practical Aspects of Load Reducing pitch control system for a 5 MW offshore wind turbine. The annual conference and exhibition of European wind energy association, pp. 101-105. 2013.
- [16] Chen, Z., Stol. K., An assessment of the effectiveness of individual pitch control on upscale wind turbines. J. Phys. Conf. Ser. 2014.
- [17] Fernando, Daniel et al., Studi Eksperimen Pengaruh Silinder Sirkular Sebagai Pengganggu Aliran Di Depan Sisi Returning Blade Terhdapar Performa Turbin Angin Tipe Savonius. J. Sains dan Seni ITS, vol. 6, no. 1, pp. 51–66, 2017.
- [18] Hamdan, Mohammad. Optimization of Small Wind Turbines using Genetic Algorithms. International Journal of Applied Metaheuristic Computing. 7. 50-65. 2016.
- [19] Afework, B., Hanania, J., Stenhouse, K., & Donev, J. *Betz Limit*. 2018.
- [20] Danang, M., & Nugroho, N. Analysis of the Installation of Public Street Lighting (PJU) at the Exit Gate of Pemalang Toll. Semarang University. 2020.
- [21] Kid Wind. Wind Energy Math Calculations: Calculating the Tip Speed Ratio of Your Wind Turbine. 1–5. 2015.
- [22] Bird, J. Basic Engineering Mathematics, published by Elsevier Ltd. 2017.
- [23] Admin. Low RPM Generators. Innotec Power PMG Technology. 2012.
- [24] Komass, T., & Sniders, A. Design and verification of vertical axis wind turbine simulation model. Engineering for Rural Development, 13, 335–340. 2014
- [25] Kumar, R., Raahemifar, K., & Fung, A. S. A critical review of vertical axis wind turbines for urban applications. Renewable and Sustainable Energy Reviews. 2014.